

Example message

cons.No.	Seg.	Example
1	UNA	UNA:+.? '
2	UNB	UNB+UNOC:3+OD012345:59:123+987654321:1:LAFES+071205:1446+144659 +++++1 '
3	UNH	UNH+12345+DESADV:D:07A:UN:GAVF11 '
4	BGM	BGM+351:::Profil+Lieferavis Nummer+9 '
5	DTM	DTM+137:20131201:102 '
6	DTM	DTM+11:20131201:102 '
7	DTM	DTM+132:20131201:203 '
8	DTM	DTM+55:20131201:203 '
9	MEA	MEA+AAX+AAD+KGM:9 '
10	MEA	MEA+AAX+AAL+KGM:9 '
11	MEA	MEA+AAX+ABJ+MTQ:9 '
12	MEA	MEA+LMT++MTR:9 '
13	MEA	MEA+AAE++PCE:9 '
14	MOA	MOA+64:90:EUR '
	SG1	
15	RFF	RFF+AAS:Transportdokumentennummer '
	SG1	
16	RFF	RFF+AH1:SON0000044215 '
	SG1	
17	RFF	RFF+AAO:12345 '
	SG1	
18	RFF	RFF+AAN:12345 '
	SG1	
19	RFF	RFF+CRN:12345 '
	SG1	
20	RFF	RFF+AVU:12345 '
	SG1	
21	RFF	RFF+PK:PACK '
	SG2	
22	NAD	NAD+SF+Identifier::91+ORGID:Address:Plant+Name1:Name2:X:X+Stree t1:Street2+City++12345+DE '
	SG3	
23	RFF	RFF+ANK:123456789 '
	SG2	
24	NAD	NAD+ST+Identifier::92+ORGID:Address:Plant+Name1:Name2:X:X+Stree t1:Street2+City++12345+DE '
25	LOC	LOC+11+Dock::92:Somewhere+AS4711 '
26	LOC	LOC+7+PoC::92:Point of Consumption '
27	LOC	LOC+13+WH:::Warehouse '

Example message

cons.No.	Seg.	Example
	SG3	
28	RFF	RFF+ANK:123456789'
	SG2	
29	NAD	NAD+BY+Plant-Code::92+ORGBY:Address:BUYID+Name1:Name2:X:X+Street1:Street2+City++12345+DE'
	SG3	
30	RFF	RFF+ANK:123789456'
	SG3	
31	RFF	RFF+VA:DE123456789'
	SG2	
32	NAD	NAD+SE+Identifier::92+ORGID:Address:Plant+Name1:Name2:X:X+Street1:Street2+City++12345+DE'
	SG3	
33	RFF	RFF+ANK:UN 987 654'
	SG3	
34	RFF	RFF+VA:DE456789'
	SG4	
35	CTA	CTA+SU+Department:Contact Name'
36	COM	COM+123abc:TE'
	SG2	
37	NAD	NAD+FW+Identifier::92+ORGID:Address:Plant+Name1:Name2:X:X+Street1:Street2+City++12345+DE'
	SG3	
38	RFF	RFF+ANK:UN 4203985'
	SG2	
39	NAD	NAD+CA+Identifier::92+ORGID:Address:Plant+Name1:Name2:X:X+Street1:Street2+City++12345+DE'
	SG3	
40	RFF	RFF+ANK:UN 89801435'
	SG2	
41	NAD	NAD+OJ+Identifier::92+ORGID:Address:Plant+Name1:Name2:X:X+Street1:Street2+City++12345+DE'
	SG2	
42	NAD	NAD+UD+Identifier::92+ORGID:Address:Plant+Name1:Name2:X:X+Street1:Street2+City++12345+DE'
	SG5	
43	TOD	TOD+6++CFR:::Hamburg'
44	FTX	FTX+HAZ+++Y'
45	FTX	FTX+AVA+++C03:X'
46	FTX	FTX+TRA++forcarrier+Carrier Comment'
47	FTX	FTX+TRA++fromcarrier+Carrier Comment'

Example message

cons.No.	Seg.	Example
	SG6	
48	TDT	TDT+12++30+++++M-SO2311 '
	SG8	
49	EQD	EQD+CN+AB12345 '
	SG10	
50	CPS	CPS+1++3 '
	SG11	
51	PAC	PAC+1+:35:AAD+BA::92+X:EP 100:SA:EP 100 B '
52	MEA	MEA+AAZ+LN+MMT:9 '
53	MEA	MEA+AAZ+WD+MMT:9 '
54	MEA	MEA+AAZ+HT+MMT:9 '
55	MEA	MEA+AAZ+ABJ+DMQ:9 '
56	MEA	MEA+LMT++MTR:9 '
57	QTY	QTY+189:5:PCE '
58	QTY	QTY+171:1:PCE '
	SG12	
59	HAN	HAN
60	FTX	FTX+PKG+++Customer package description'
	SG13	
61	PCI	PCI+17+Free Text:Free Text:Free Text++5J::5'
	SG14	
62	GIR	GIR+3+123456:AT'
	SG15	
63	GIN	GIN+ML+1013'
	SG15	
64	GIN	GIN+AW+12345+12346+12347+12348+12349'
	SG16	
65	COD	COD+NO'
66	MEA	MEA+AAZ+AAB+KGM:9'
67	MEA	MEA+AAZ+AAA+KGM:9'
	SG11	
68	PAC	PAC+5+:35+PE::92+X:EP 100:SA:EP 100 B '
69	MEA	MEA+AAZ+LN+MMT:9'
70	MEA	MEA+AAZ+WD+MMT:9'
71	MEA	MEA+AAZ+HT+MMT:9'
72	MEA	MEA+AAZ+ABJ+DMQ:9'
73	QTY	QTY+171:9'
	SG12	
74	HAN	HAN

Example message

cons.No.	Seg.	Example
75	FTX	FTX+PKG+++Customer package description'
	SG13	
76	PCI	PCI+17+++5J::5'
	SG16	
77	COD	COD+NO'
78	MEA	MEA+AAZ+AAB+KGM:9'
	SG10	
79	CPS	CPS+2++1'
	SG11	
80	PAC	PAC+9+:35:AAC+PE::92:X+X:KLT 4711:SA:KLT 4711 B'
81	MEA	MEA+AAY+G+KGM:9'
82	MEA	MEA+AAY+AAL+KGM:9'
83	MEA	MEA+AAY+LN+MMT:9'
84	MEA	MEA+AAY+WD+MMT:9'
85	MEA	MEA+AAY+HT+MMT:9'
86	MEA	MEA+AAY+ABJ+LTR:9'
87	QTY	QTY+52:9:PCE'
88	QTY	QTY+171:1:PCE'
	SG12	
89	HAN	HAN
90	FTX	FTX+PKG+++Customer package description'
	SG13	
91	PCI	PCI+17+Additional Part Information++1J::5'
	SG14	
92	GIR	GIR+1+Charge:BX'
93	DTM	DTM+94:20130807:102'
94	DTM	DTM+94:20130807:102'
	SG14	
95	GIR	GIR+3+12345:AW'
	SG14	
96	GIR	GIR+7+2:AM'
	SG15	
97	GIN	GIN+ML+123'
	SG15	
98	GIN	GIN+AL+AB1+X'
	SG15	
99	GIN	GIN+BN+SN1+SN2+SN3+SN4+SN5'
	SG11	
100	PAC	PAC+9+:37:AAB+PE::92:X:KLT 4711:SA:KLT 4711 B'

Example message

cons.No.	Seg.	Example
101	MEA	MEA+AAY+T+KGM:9'
102	MEA	MEA+AAY+LN+MMT:9'
103	MEA	MEA+AAY+WD+MMT:9'
104	MEA	FTX+PKG+++Customer package description'
	SG12	
105	HAN	HAN
106	FTX	FTX+PKG+++Customer package description'
	SG11	
107	PAC	PAC+9+:35+PE::92+X:KLT 4711:SA:KLT 4711 B'
	SG12	
108	HAN	HAN
109	FTX	FTX+PKG+++Customer package description'
	SG17	
110	LIN	LIN+++1234567890:IN'
111	PIA	PIA+1+Supplier Material ID:SA'
112	IMD	IMD++8+19::272:Customer Article Description:Supplier Article Description'
113	IMD	IMD++11+19::272:Commodity Description::de'
114	MEA	MEA+PD+AAL+KGM:5'
115	MEA	MEA+PD+G+KGM:5'
116	QTY	QTY+12:9:PCE'
117	QTY	QTY+131:9:PCE'
118	ALI	ALI+DE+N+DE+Y+S'
119	DTM	DTM+94:CCYYMMDD:102'
120	DTM	DTM+36:CCYYMMDD:102'
121	NAD	NAD+MF+123456789::16++Name1:Name2:Name3:Name4+Street1:Street2+City++12345+DE'
122	FTX	FTX+LIN+++Text:Text:Text:X'
123	FTX	FTX+LIN+QTY++PRS1:111'
124	FTX	FTX+LIN+QTY++PRS2:111'
125	FTX	FTX+LIN+QTY++PRS3:111'
126	FTX	FTX+LIN+QTY++PRS4:111'
127	FTX	FTX+LIN+QTY++PRS5:111'
128	FTX	FTX+FXA+++Text:Text:Text:Text:Text'
129	FTX	FTX+FXB+++Text:Text:Text:Text:Text'
130	FTX	FTX+FXC+++Text:Text'
131	FTX	FTX+FXD+++Date:Date'
	SG18	
132	RFF	RFF+AAU:Delivery note number:1'
133	DTM	DTM+171:20131201:102'

Example message

cons.No.	Seg.	Example
	SG18	
134	RFF	RFF+BC:FC12345'
	SG18	
135	RFF	RFF+VC:DC12345678'
	SG18	
136	RFF	RFF+AAN:JitCall:1'
	SG18	
137	RFF	RFF+ON:OrderNumber:1'
	SG18	
138	RFF	RFF+AWU:Kanban'
	SG18	
139	RFF	RFF+IV:Invoice'
140	DTM	DTM+171:20131201:102'
	SG18	
141	RFF	RFF+LI:ShipmentID'
142	DTM	DTM+171:20131201:102'
	SG18	
143	RFF	RFF+ACE:Consignment'
144	DTM	DTM+171:20131201:102'
	SG18	
145	RFF	RFF+WR:WR12345'
	SG18	
146	RFF	RFF+AOL:12345'
	SG19	
147	DGS	DGS++N:Y+1234'
148	FTX	FTX+HAZ+++Text:Text'
149	FTX	FTX+AAN++Y+HazDescription:HazSubclass:HazPackingGroup'
	SG20	
150	LOC	LOC+11+:::Entladeort'
	SG20	
151	LOC	LOC+159+:::Interner Bestimmungsort'
152	UNT	UNT+112+12345'
153	UNZ	UNZ+1+144659'